

DAB Starpoint Combiner 400W



RACDA 6 x cavity 100 mm , 1 feedback

combining of 2-6 transmitters to 1 output

all connectors DC - short

temperature stabilized

tuned to desired freq at our factory

2 transmitters , all DIN7-16 , 1 feedback code:

RACDA100-I33-O3-FB1-400W-010

specification :

RACDA100	... 100 mm cavities
Max RMS power per input	... 400W
type	... starpoint
temperature stability	... 1kHz/°C
operating environment temperature	... -5 to 50°C
tuned channel width	... 1.54 MHz
tunable range	... 174-240 MHz
insertion loss	... 1 dB
isolation between channels	... > 30 dB
input reflections	... < -25 dB
minimal frequency spacing between inputs	... 3.42 MHz
filter feedback number	... 1
dimensions of 2 input version	... 500x352x770 mm
weight of 2 input version	... 39 kg